

FLM-325-I4-A Contact Monitors

www.boschsecurity.com



BOSCH
Invented for life



- ▶ Monitors Normally Open (NO) or Normally Closed (NC) contacts
- ▶ Monitored Normally Closed (NC) contacts can be configured with or without EOL resistor
- ▶ Module address programming with the D5070 Analog Device Programmer
- ▶ Bi-colored LED provides module status
- ▶ Digital data communications and power over a two-wire circuit

The FLM-325-I4-A and FLM-325-I4-AI modules are used to connect standard Normally Open or Normally Closed dry contact types of fire alarm devices such as pull stations or water flow devices. The modules are mounted to a cover plate for a 4-inch square or double-gang electrical back box. A bi-colored LED provides the module status.

Functions

Address Range

Contact Monitor modules must be programmed with a unique address. All devices connected to module appear only as one single address at the fire panel. The modules are compatible with 254 addresses.

Status Conditions

The module supervises the wiring to the contact with an EOL resistor. If a fault condition occurs, the module sends a trouble signal to the fire panel. If a status change occurs, the module sends an interrupt signal to the fire panel indicating that an alarm has occurred.

Certifications and approvals

Region	Certification	
USA	UL	UOXX: Control Unit Accessories, System (ANSI/UL 864)
	CSFM	see our website
	FDNY-CoA	#6101

Installation/configuration notes

Compatibility Information

The following products are compatible with the modules:

Category	Product ID	Product Description
Fire Panels	FPA-1000 series	Analog Addressable Fire Panels
Programmer	D5070	Analog Device Programmer

Data Circuit Length

Data (or polling) circuit length is the distance over the circuit wire from the connection at the fire panel to the most distant device and back to the fire panel. Data circuit length must include the distance to any

device connected to the circuit in a T-tap. The screw terminals can accept 14 AWG (ISO 2.5 mm²) wire; thinner wire can be used, but this reduces the allowable length of the circuit.

Initiating Device Circuit Connections

The initiating device circuit can use any number of UL listed Normally Open (NO) contact closure devices. Device circuit wiring must not exceed 50 Ω . Install contact closure devices according to the manufacturer's installation instructions. All wiring must be supervised and power-limited.



Notice

Do not mix fire alarm initiating and supervisory devices on the same module.

Parts included

Quant.	Component
1	FLM-325-I4-A Family Contact Module
1	EOL resistor, 10 k Ω
1	Wall plate
1	Hardware pack
1	Literature pack

Technical specifications

Power Requirements

Input Voltage	25.3 VDC to 39 VDC
Current Consumption	
• Nominal:	0.63 mA
• Maximum:	6.3 mA

Resistance

• End of Line Device	10 k Ω , 0.25 W per resistor
• Initiating Device Circuit	Less than 50 Ω

Mechanical Properties

Dimensions (H x W x D):	4.7 in. x 4.2 in. x 1.4 in. (11.9 cm x 10.7 cm x 3.6 cm)
Weight	20 oz (567 g)
Color	Ivory
Material	ABS Blend
Response Time	2 sec

Environmental Considerations

Operating Temperature	+32°F to +120°F (0°C to +49°C)
Relative Humidity	Up to 90 %, non-condensing

Ordering information

FLM-325-I4-A Contact Monitor 4-inch Class A

Can be wired for Class A or Class B circuits; mounted to a cover plate for a 4-inch square or double gang electrical back box; bi-colored LED provides module status; compatible with 254 addresses
Order number **FLM-325-I4-A**

FLM-325-I4-AI Contact Monitor 4-inch Class A with Isolator

Can be wired for Class A or Class B circuits; has built-in short circuit isolator circuitry; mounted to a cover plate for a 4-inch square or double gang electrical back box; bi-colored LED provides module status; compatible with 254 addresses
Order number **FLM-325-I4-AI**

Represented by:

Americas:

Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
security.sales@us.bosch.com
www.boschsecurity.us

Europe, Middle East, Africa:

Bosch Security Systems B.V.
P.O. Box 80002
5617 BA Eindhoven, The Netherlands
Phone: + 31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:

Robert Bosch (SEA) Pte Ltd, Security
Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

China:

Bosch (Shanghai) Security Systems Ltd.
201 Building, No. 333 Fuquan Road
North IBP
Changning District, Shanghai
200335 China
Phone +86 21 22181111
Fax: +86 21 22182398
www.boschsecurity.com.cn

America Latina:

Robert Bosch Ltda Security Systems Division
Via Anhanguera, Km 98
CEP 13065-900
Campinas, Sao Paulo, Brazil
Phone: +55 19 2103 2860
Fax: +55 19 2103 2862
latam.boschsecurity@bosch.com
www.boschsecurity.com